

Yoswit Smart TRIAC Dimmer Switch Module Datasheet

Model: YO619d (R2)

Revised: 01-12-2024




The Perfect Choice for Advanced Lighting Control

Yoswit Smart TRIAC Dimmer Switch Module features a mini design that hides in the wire box, effortlessly replacing your original wall switches while allowing you to control your lights through the Yoswit app. It seamlessly connects to traditional wiring and is compatible with leading-edge and trailing-edge phase-cut dimmable AC bulbs. Its wide dimming range ensures flicker-free light bulbs even at low dimming levels. Enjoy wireless control without a hub and extend control distance of the Yoswit device network with our proprietary topology. After connecting to a hub, it integrates with smart speakers and accesses remote control. Featuring brightness adjustment, scene modes, and low power consumption, it provides unparalleled lighting control. Create a smart living symphony with Yoswit's intelligent linkage among products.

Connection1 : TRIAC Dimmable Bulb

Connection2 : TRIAC Dimmable Driver




Key Features and Benefits

- No Switch Box Dependency
- High Compatibility Dimmer
- Brightness Adjustment for Customized Lighting Levels
- Scene Modes for Setting Different Lighting Scenarios
- Built-in Timer for Automation
- No Hub Required for Wireless Control
- Connects to a Hub for Remote Control
- Proprietary Topology for Mesh-like Network

Various Customized Products

We offer a comprehensive selection of smart home products that are seamlessly adapted to the usage standards and various socket types in different countries, ensuring a smooth installation process for all users. With extensive compatibility, our products enable you to control a diverse range of household appliances, including lighting, air conditioning, and TV.



Yoswit App

You can download our app to implement the following functions via Bluetooth and WiFi to control the Yoswit switches.



Time Setting



Scene Mode



Device Network



Away Detection



Password Protection



Network Control



Apple Siri



Google Assistant




IFTTT

Depends on Yoswit Bridge Solutions.



Product Specifications

Specifications:



Electrical	
Input Voltage	100-240V AC (50/60Hz)
Frequency	60/50Hz Auto Detected at Power-up
Resistive Load Current	Max. 400W
Inductive Load Current	Max. 400W
Standby Power	<0.1W

Wireless	
Frequency	2.4GHz
Connection	BLE 4.2
Range	Open Area: >50m / Interior: 3-20m


General Specifications

Product Name	Yoswit Smart TRIAC Dimmer Switch Module
Model	YO619d (R2)
EAN / UPC	EAN: 0765756498180 / UPC: 765756498180
Revision	V1.0
Compliance	CE, FCC, RoHS
Manufacturer	Designed by Yoswit in Hong Kong, China / Assembled in Guangdong, China
Warranty	Two Year Limited Warranty (*Details available on the Product Warranty and Limitations of this datasheet)

Mechanical

Storage Conditions	-20°C to 60°C
Operation	APP
Operating Temperature	-10°C to 50°C
Operating Humidity	0-90% RH, Non-Condensing

Product Package



Outer Box



Quantity Per Box: 40 Pack / Box
Measurement: 58 x 31 x 23.5 (cm)

Product Warranty and Limitations

Yoswit brand products guarantee for a period of 2 years warranty from the date of purchase. During the warranty period and in the event that a defective product is identified (non-human factors), Yoswit will provide free maintenance. Damage beyond the warranty period or caused by improper use is not covered within the warranty, Yoswit will not bear any responsibility for repair, and will still provide users with a lifelong maintenance of paid services. If the products need to be repaired or returned to our company, an appropriate fee should be charged based on specific situation to cover the cost of replacement. Regardless of the warranty status, all shipping costs are borne by users.

LINCOGN TECHNOLOGY CO. LIMITED

Address: Room 202, 2/F, Building No. 19 West Science and Technology Avenue, Science Park, Shatin, N.T., Hong Kong
info@yoswit.com | Tel: (852) 3996 9396 | Fax: (852) 3119 8778 | www.yoswit.com